

84RX



HONEYWELL 84RX

PC-Compatible Silent-Tactile Keyboard RX Series

- IBM PC, PC-XT, PC-AT plug compatible electrical interface (auto-sensing)
- Traditional IBM PC-AT 84-key array
- Status LEDs for CAPS, NUM and SCROLL Lock
- Operator-preferred silent-tactile feel
- Proven membrane switch construction
- Two-position tilt angle enclosure adjustment (6° and 13°)
- 3-year warranty
- UL recognized and CSA certified
- FCC Class B Certification

Honeywell 84RX is a plug compatible replacement for IBM's PC, PC-XT, PC-AT and many IBM PC compatible systems. Its auto-sensing micro processor interrogates the PC system on power up and selects the proper electrical interface, eliminating the need for selector switches or separate keyboards for each system. Status LEDs for Caps Lock, Num Lock and Scroll Lock tell at a glance which modes these keys are in, greatly reducing accidental entry of false data or commands.

The keyboard features silent-tactile construction which provides quiet operation and positive tactile feel that helps reduce user fatigue and decrease errors. It has a 6-foot (practical extended length) coiled cord and a high strength, injection molded plastic enclosure with a driftwood finish.

The 84RX carries a 3-year limited warranty and meets FCC Class B Certification.

Honeywell

84RX

RX Series
PC-Compatible
Silent-Tactile
Keyboard



1. Cable assembly: 5 conductor (24 AWG) round cable with a Switchcraft (05GM5M) or equivalent interface connector. 6-foot (practical extended length - min.) coiled cable. Driftwood cable and enclosure (Color No. 8987).
2. Adjustable feet (2) allow operator to have two height settings of 6° and 13°.
3. Overall dimensions: 18.26 in. (L) x 7.62 in. (W).


Specifications

Electrical Characteristics

Input Power: 5 VDC \pm 10% @ 350 mA max.

Data Transmission: IBM Personal Computer synchronous (occurs on a common clock and data line).

Connector Termination



Pin No.

Signal

1	CLOCK
2	DATA
3	RESET (OPTIONAL)
4	GROUND
5	+5VDC

Catalog Listing

84RX43S-5E

Sales and Service

Honeywell RX Keyboards are available from:

For additional information or assistance, please write or call us at:
Honeywell Keyboard Division, 4171 North Mesa, Bldg. D, El Paso, TX 79902
1-800-445-6939, in Texas call collect: 915/543-5566

Together, we can find the answers.

Honeywell